

**HUNTSVILLE UTILITIES
APPROVED METER SOCKET LIST**

SINGLE PHASE

SIZE	USE	MANUFACTURER	CATALOG NUMBER
60 Amp	OH	Milbank	AP2300-03
100 Amp	OH/UG	Durham	UTRS101B
100 Amp	OH/UG	Cutler-Hammer	UTRS101BCH
100 Amp	OH/UG	Square D	UTRS101BSQD
100 Amp	OH/UG	Midwest	UTRS101BMEP
100 Amp	OH/UG	Durham	UMT RS212ASQD
100 Amp	OH/UG	Durham	1005647A
125 Amp	OH/UG	Milbank	U7487-RL-TG
150 Amp	OH	Durham	UTRS502B
150 Amp	OH	Cutler-Hammer	UTRS502BBCH
150 Amp	OH	Square D	UTRS502BBSQD
150 Amp	OH	Midwest	UTRS502BBMEP
150 Amp	OH	Milbank	U7262-RL-TG
150 Amp	OH/UG	Durham	UTRS512B
150 Amp	OH/UG	Cutler-Hammer	UTRS512BCH
150 Amp	OH/UG	Square D	UTRS512BSQD
150 Amp	OH/UG	Midwest	UTRS512BMEP
150 Amp	OH/UG	Milbank	U8084-XL-TG
200 Amp	OH	Durham	UTRS202B
200 Amp	OH	Cutler-Hammer	UTRS202BCH
200 Amp	OH	Square D	UTRS202BSQD
200 Amp	OH	Midwest	UTRS202BMEP
200 Amp	OH	Durham	UTRS203B
200 Amp	OH	Cutler-Hammer	UTRS203BCH
200 Amp	OH	Square D	UTRS203BSQD
200 Amp	OH	Midwest	UTRS203BMEP
200 Amp	OH	Milbank	U7021-RL-TG
200 Amp	UG	Durham	UTRS220A
200 Amp	UG	Cutler-Hammer	UTRS220ACH
200 Amp	UG	Square D	UTRS220ASQD
200 Amp	UG	Midwest	UTRS220AMEP
200 Amp	UG	L & G	UAS877-PG
200 Amp	UG	Siemens	SUAS877-PG
200 Amp	UG	Milbank	U2986-O
200 Amp	UG	Milbank	U1980-O

NOTE : The categories OH and UG imply OH only and UG only respectively. The OH/UG category was created for listing meter sockets that meet both criteria.

In the event a meter socket not listed herein is installed, the service will not be connected until it is replaced with a properly installed approved meter socket.

**HUNTSVILLE UTILITIES
APPROVED METER SOCKET LIST**

SINGLE PHASE (cont)

320 Amp	OH	Durham	UT-H4300T
320 Amp	OH	Cutler-Hammer	UT-H4300TCH
320 Amp	OH	Square D	UT-H4300TSQD
320 Amp	OH	Midwest	UT-H4300TMEP
320 Amp	OH	Milbank	NU1079-R

320 Amp	UG	Durham	UT-H4320A
320 Amp	UG	Cutler-Hammer	UT-H4320ACH
320 Amp	UG	Square D	UT-H4320ASQD
320 Amp	UG	Midwest	UT-H4320AMEP
320 Amp	UG	Milbank	NU1797-O- K3L-K2L

320 Amp	OH/UG	Durham	UT-H4330T
320 Amp	OH/UG	Cutler-Hammer	UT-H4330TCH
320 Amp	OH/UG	Square D	UT-H4330TSQD
320 Amp	OH/UG	Midwest	UT-H4330TMEP
320 Amp	OH/UG	L & G	47604-02
320 Amp	OH/UG	Siemens	S47604-02
320 Amp	OH/UG	Milbank	NU3313-X

Retrofit Bolt in

Discontinued

400 Amp	OH/UG	L & G	9810-8507
400 Amp	OH/UG	Siemens	S9810-8507
NOTE: The above retrofit meter main equipment can ONLY be used by special permission, at the discretion of Huntsville Utilites. Its approval will be dictated by the inability to physically install other alternatives in the available space.			

Contact Engineering services for single phase services exceeding 320 amps

Bolt-in

Discontinued

400 Amp	OH/UG	L & G	9810-9507
400 Amp	OH/UG	Siemens	S9810-9507

Contact Engineering services for single phase services exceeding 320 amps

600 Amp	UG	L & G	9810-9507
600 Amp	UG	Siemens	S9810-9507

Contact Engineering services for single phase services exceeding 320 amps

METER MAIN

200 Amp	OH/UG	Milbank	U3795-200-XL
200 Amp	OH/UG	Milbank	UA5896 PXL-200
320 Amp	UG	Milbank	U4031-O-2/200
320 Amp	OH/UG	Milbank	U5059 X-2/200

Retrofit Meter Main

200 Amp	OH/UG	Siemens	MM0202B1200R
200 Amp	OH/UG	Murray	JC0202B1200R
NOTE: The above retrofit meter main equipment can ONLY be used by special permission, at the discretion of Huntsville Utilites. Its approval will be dictated by the inability to physically install other alternatives in the available space.			

NOTE: The categories OH and UG imply OH only and UG only respectively. The OH/UG category was created for listing meter sockets that meet both criteria.

NOTE: In the event a meter socket not listed herein is installed, the service will not be connected until it is replaced with a properly installed approved meter socket.

**HUNTSVILLE UTILITIES
APPROVED METER SOCKET LIST**

SINGLE PHASE (cont)

METER MAIN W/BRANCH BREAKER PROVISION

100 Amp	OH	Durham	UP140WO(*)
200 Amp	OH	Durham	UW260WO(*)
200 Amp	OH/UG	Siemens	MC0816B1200RCT
200 Amp	OH/UG	Murray	JA0816B1200RCT
200 Amp	OH/UG	Milbank	U5897-PXL-200

RETROFIT METER MAIN W/BRANCH BREAKER PROVISION

200 Amp	OH/UG	Siemens	MC0816B1200RTH
200 Amp	OH/UG	Murray	JA0816B1200RTH
NOTE: The above retrofit meter main equipment can ONLY be used by special permission, at the discretion of Huntsville Utilites. Its approval will be dictated by the inability to physically install other alternatives in the available space.			

MOBILE HOME METER PEDESTALS

200 Amp	UG	Milbank	U5136-O-200S
200 Amp	UG	Siemens	MP200

TEMPORARY CONSTRUCTION SERVICE

100 Amp	OH/UG	Milbank	USE-M-38GR
100 Amp	OH/UG	Cutler-Hammer	CHR3N7N7NS
100 Amp	OH	Midwest	MP78C
100 Amp	OH	Siemens	P77RTS

NOTE (TC1): Huntsville Utilities does not repair or replace parts on customer owned temporary construction service sockets or devices.

NOTE (TC2): The temporary service equipment listed above are pre-assembled packages developed for convenience. Any service appropriate approved socket can be used for temporary service in conjunction with appropriate service entrance and power distribution equipment. (example, a 100 amp approved single phase socket such as the Durham UTRS101B with a 60 or 100 amp weatherproof main breaker, and appropriate weatherproof distribution breakers and plugs, assembled and wired in accordance with the current National Electric Code, and applicable local codes and restrictions.

NOTE: The categories OH and UG imply OH only and UG only respectively. The OH/UG category was created for listing meter sockets that meet both criteria.

In the event a meter socket not listed herein is installed, the service will not be connected until it is replaced with a properly installed approved meter socket.

**HUNTSVILLE UTILITIES
APPROVED METER SOCKET LIST**

THREE PHASE

100 Amp	OH	Milbank	NU8100-RL-TG
---------	----	---------	--------------

100 Amp	UG	Milbank	NU9321-XL
---------	----	---------	-----------

200 Amp	OH	Durham	UT-H7203B
200 Amp	OH	Cutler-Hammer	UT-H7203BCH
200 Amp	OH	Square D	UT-H7203BSQD
200 Amp	OH	Midwest	UT-H7203BMEP
200 Amp	OH	Milbank	U4700-RL
200 Amp	OH	Durham	UT-H7213B
200 Amp	OH	Square D	UT-H7213BSQD
200 Amp	OH	Midwest	UT-H7213BMEP
200 Amp	OH	Cutler-Hammer	UT-H7213BCH
200 Amp	OH	Milbank	U4701-RL

200 Amp	OH/UG	L & G	9804-9141
200 Amp	OH/UG	Siemens	S9804-9141
200 Amp	OH/UG	Milbank	U1493-X

400 Amp	OH/UG	L & G	9817-8512
400 Amp	OH/UG	Siemens	S9817-8512
400 Amp	OH/UG	L & G	9817-9504
400 Amp	OH/UG	Siemens	S9817-9504

Contact Engineering services for three phase services exceeding 200 amps

600 Amp	UG	L & G	9817-9504
600 Amp	UG	Siemens	S9817-9504

Contact Engineering services for three phase services exceeding 200 amps

**NOTE: For 480Y/277 volt service, only the following sockets are acceptable:
(7 terminal self-contained):**

200 Amp	OH	Durham	UT-H7213B
200 Amp	OH	Cutler-Hammer	UT-H7213BCH
200 Amp	OH	Square D	UT-H7213BSQD
200 Amp	OH	Midwest	UT-H7213BMEP
200 Amp	OH	Milbank	NU4701-RL-TG

200 Amp	OH/UG	L&G	9804-9141
200 Amp	OH/UG	Milbank	U1493-X

For commercial services larger than 200 amps, and all services over 320 amps, contact Electric Engineering Services for service details, then contact the Electric Meter Shop for socket and instrumentation information.

NOTE: The categories OH and UG imply OH only and UG only respectively. The OH/UG category was created for listing meter sockets that meet both criteria.

In the event a meter socket not listed herein is installed, the service will not be connected until it is replaced with a properly installed approved meter socket.

NOTE: House power service equipment has been removed from the approved list due to code conflicts. Meter-main combination units with branch breaker provisions are now used instead of those products.

Discontinued